





SCAPINI S2

The lighting with assertive design Medium size version





















SCAPINI S2

| Range | Accent decorative luminaire |
|--|---|
| | Designed by Benoit Lalloz |
| | |
| Description | Body in anodised aluminium (natural or black) |
| | Directional bracket |
| Dimensions | Can dimensional desputing |
| Dimensions | See dimensional drawing |
| Net Weight | 0.266 kg |
| | |
| LED characteristics | 1 LED: 3000K - 4000K (other LED colours upon request) |
| Optical beam | 15°- 50° (other optical beam upon request) |
| | |
| Connection | Delivered with 0.5m standard cable (more length upon request) |
| | Connection in series on external constant current driver |
| Compared monage complex QFQreA FQQreA | |
| Separate power supply | 350mA - 500mA |
| LED power | 350mA: 4.8W |
| | 500mA: 7.2W |
| | The product must be installed into a ventilated area. Any use with an ambient |
| Use limitations | temperature higher than the specified ambient temperature (Ta) would lead to a more |
| | rapid mortality of the product and the withdrawal of our guarantees. |
| | The drivers, if not delivered by LOuss, must be approved before use. |
| Warranty | Life span: L80B10 at 50,000 hours (80% remaining flux) at 25°C ambient temperature. |
| | 3-year parts and labour warranty. |
| | The warranty does not apply to products that have been opened, modified or repaired and does not cover the effects of a wrong connection, careless, abusive handling, |
| | overvoltage, lighting injury, as well as the normal wear of the product. |
| | All products are electrically tested and received a functional burn-in. |
| All the connections have to be made before newering up | |

All the connections have to be made before powering up, otherwise the luminaire could be seriously damaged.

Wuss

Last update: 20/09/2018

Firalux & LOuss brands